



Note: \*Above shown Power supply image is for representation purpose only

- ☺ HIGH EFFICIENCY UP TO 90%
- ☺ BUILT IN REMOTE SENSE FUNCTION
- ☺ 1 YEAR WARRANTY

Contact :

## RETRACK SYSTEMS

#1038,'Hombelaku',  
11<sup>th</sup> main, Hampinagar,  
Vijayanagar 2<sup>nd</sup> Stage,  
Bangalore – 560 040.  
Mob:98447 59090 / 98863 59090  
Web-[www.retracksystems.com](http://www.retracksystems.com)  
Mail-[sales@retracksystems.com/](mailto:sales@retracksystems.com)  
[retracksystems@gmail.com/](mailto:retracksystems@gmail.com)  
[retrack\\_systems@yahoo.com](mailto:retrack_systems@yahoo.com)

### OUR OTHER PRODUCTS RANGES;



500A Regulated Power supply



Laboratory Power Supplies



Auto Transformers



R/L/C Load Bank



Mil Grade Power Supplies

INPUT	
Voltage Range	230V AC ± 10%
Frequency Range	50Hz, Single Phase
Power Factor	0.95/230VAC at full load
Efficiency	95%
OUTPUT- SINGLE CHANNEL	
DC Voltage	0 to 300V (Variable)
Rated Current	0 to 10A (Variable)
TECHNICAL SPECIFICATION	
<b>PROTECTION</b>	<b>Ripple &amp; Noise</b> <10mVrms
Overload / Short Circuit	Storage Temperature 0°C to 65 °C
<b>Operating Temperature</b> 0°C - 50°C	
<b>Regulation CV Mode</b> Line & Load regulation better than ±0.05%	<b>Regulation CC Mode</b> Line & Load regulation better than ±0.1%
<b>Stability After 8Hrs</b> 0.05% ±5mV	<b>Transient Recovery</b> 50µs
<b>Indications:</b> 3Digit LED Digital meters for Voltage & Current, Accuracy:0.5%±2 Counts	<b>Output Control</b> Course and Fine Single turn Potentiometers for V & I
FEATURES	
Good Regulation	Low Ripple & Noise
Constant Voltage/Current limited	Continuously Variable Voltage
Continuously Variable maximum Current limit from 10% to 110% of full load	Electrically Floating output. Can be floated up to 300V off ground
LED indication for O.L.	Soft start Circuit
Accessories: User Manual with Warranty Certificate & Q.C. Test report.	
RUGGED AND AESTHETIC MECHANICAL AND ELECTRICAL DESIGN	

**CUSTOM MADE POWER SUPPLIES ARE ALSO AVAILABLE**

